

DECK LITE LUMINAIRE INSTALLATION INSTRUCTIONS



NOTE: THESE INSTRUCTIONS MUST NOT CONTRAVENE YOUR LOCAL ELECTRICAL AUTHORITY REGULATIONS, WITH WHICH ALL INSTALLATIONS HERE IN MUST COMPLY. PLEASE KEEP INSTRUCTIONS FOR FUTURE REFERENCE.

The secondary wiring supplied with this light fixture is intended for shallow burial - less than 6" (152mm) **DO NOT** install this light fixture within 10 feet (3 mtr.) of a pool, spa or fountain.

Remove stainless steel grub screws and detach end cap. Apply silicon around the one inch hole in the bottom of the end cap and mount end cap to deck/tiles etc, using stainless steel screws provided. Connect luminaire making a waterproof connection using heavy walled adhesive lined heat shrink, to the low voltage cable. Secure the luminaire to the end cap using the stainless steel grub screws provided.

NOTE - do not use the anti glare hood to remove lens section for lamp replacement. Place hand on acrylic lens and unscrew.

Recommendation:

Run all low voltage cables in flexible conduit for extra protection.

It is recommended that high quality halogen capsules are used when replacing existing capsules.

HALOGEN CAPSULE CHANGING

CAUTION: Make sure that the power to the luminaire is switched off before attempting to change the lamp.

Beware of hot luminaire and lamp. Make absolutely sure when changing lamps that the correct wattage lamp is installed.

WARNING: DO NOT touch halogen capsule with bare fingers, leave plastic bag over the capsule & push into the lamp holder. Then remove plastic bag before switching fitting on. Maximum Wattage 20watt G4 Halogen Capsule.

INSTRUCTIONS PERTAINING TO A RISK OF FIRE, OR INJURY TO PERSONS IMPORTANT SAFETY INSTRUCTIONS

Lighted lamp is HOT!

WARNING - To reduce the risk of FIRE OR INJURY TO PERSONS:

Turn off / unplug and allow to cool before replacing lamp.


Lamp gets HOT quickly! Contact only switch/plug when turning on.

DO NOT touch hot lens, guard or enclosure.

Keep lamp away from materials that may burn.

DO NOT touch the lamp at any time. Use a soft cloth. Oil from skin may damage lamp.

DO NOT operate the luminaire fitting with a missing or damaged lens.



THE "MOUSE LITE™" LUMINAIRE INSTALLATION INSTRUCTIONS



NOTE: THESE INSTRUCTIONS MUST NOT CONTRAVENE YOUR LOCAL ELECTRICAL AUTHORITY REGULATIONS, WITH WHICH ALL INSTALLATIONS HERE IN MUST COMPLY. PLEASE KEEP INSTRUCTIONS FOR FUTURE REFERENCE.

The secondary wiring supplied with this light fixture is intended for shallow burial - less than 6" (152mm). Do not install this light fixture within 10 feet (3 mtr.) of a pool, spa or fountain.

The Mouse Lite™ is designed as a surface mount luminaire. Unscrew the mounting plate from the luminaire. Apply sufficient sealant to the groove on the back of the mounting plate to seal against the wall. Screw the mounting plate to the wall. Make a waterproof connection using heavy walled adhesive lined heat shrink, between the luminaire cables and the low voltage supply cables. Check that the gasket is in the correct position. Screw the luminaire onto the back plate.

Warning - Take care to place luminaire in a suitably safe position, due to operating temperature of the luminaire.

Recommendation:

It is recommended that high quality halogen capsules are used when replacing existing capsules.

HALOGEN CAPSULE CHANGING

CAUTION: Make sure that the power to the luminaire is switched off before attempting to change the lamp.

Beware of hot luminaire and lamp. Make absolutely sure when changing lamps that the correct wattage lamp is installed.

WARNING: DO NOT touch halogen capsule with bare fingers, leave plastic bag over the capsule & push into the lamp holder. Then remove plastic bag before switching fitting on. Maximum Wattage 10watt G4 Halogen Capsule.

Stainless Steel Maintenance: To maintain the finish of 316 stainless steel it is recommended to wash the luminaire with water from time to time to stop salt and corrosive elements building up. If tea staining appears, a commercially available stainless steel cleaner is recommended to remove this staining.

INSTRUCTIONS PERTAINING TO A RISK OF FIRE, OR INJURY TO PERSONS IMPORTANT SAFETY INSTRUCTIONS

Lighted lamp is HOT!

WARNING - To reduce the risk of FIRE OR INJURY TO PERSONS:

Turn off / unplug and allow to cool before replacing lamp.

Lamp gets HOT quickly! Contact only switch/plug when turning on.

DO NOT touch hot lens, guard or enclosure.

Keep lamp away from materials that may burn.

DO NOT touch the lamp at any time. Use a soft cloth. Oil from skin may damage lamp.

DO NOT operate the luminaire fitting with a missing or damaged lens.

